

DD-WRT Wireless-N Broadband Router Setup Instructions




Step 1: Connect the Antenna



Step 2: Connect the power



Step 3: Connect the ethernet cable to the blue WAN port




Step 4: Now on your ADSL or cable modem connect the other end of the Ethernet cable

Notes: if you have a cable modem make sure the cable line is connected to the cable modem
if you have an ADSL modem make sure your telephone line is connected to the modem

Step 5: make sure that you have connected your router and modem's power (both ends)


Step 6: if your desktop or laptop computer does not have a wireless card install it now




Step 7: turn on your computer and select the dd-wrt wireless access point from your distribution's network applet

Step 8: to enable security on your router and access other configuration information open your web browser and enter the following into the address bar: 192.168.1.1







Step 9: to setup wireless security click on the wireless tab



Step 10: when prompted for a user name/password enter admin (this is the user name and password)



Step 11: Select the wireless security tab



Step 12: select your preferred settings and enter a password, save, and apply

Step 13: repeat step 6 except this time with the password you have just setup